

# Mini Bulletin XRX15I WorkCentre 6400 R14-12 SPAR Release Release 061.070.105.03600



Release Date: February 2015

Version 1.0

## Software Release Details

**If your software is higher or equal to the versions listed below no action is needed. Otherwise, please review this bulletin and consider taking actions as suggested.**

Component	Version
System Software	061.070.105.03600

## Purpose

This Bulletin is ONLY intended for the specific security problem(s) identified below. The problem(s) identified has been rated as a criticality level of **IMPORTANT**

- SSLv3 POODLE (CVE-2014-3566) and OpenSSL MiTM (Man in the Middle) vulnerabilities addressed

## Installation Notes

The Software is located here: <http://www.support.xerox.com/support/all-products/file-download/enus.html?contentId=130820>

The installation instructions are attached

## Installation Instructions

### Read before beginning the firmware update:

- Do not interrupt system once download is in process. Interruptions or loss of power may corrupt the engine firmware and render the system temporary unusable. (Service repair may be required to return the system to a working condition.)
- Some of the device's settings may be changed from their present value back to the factory default values by the firmware update. It is recommended customers save the configuration page and use it as a reference to restore the device's settings after the firmware update is complete.

### To print the configuration page:

1. Press the Machine Status button on the device control panel.
2. Press the Information Pages button.
3. Select Configuration Report and press Print.

Note: The firmware versions currently installed are displayed on the left column on the first page, under the Software Versions heading.

### To download a file to the device using CentreWare Internet Services (Windows and Mac):

NOTE: CWIS can only be accessed if the device is connected to a network that utilizes the TCP/IP protocol. The device must also contain a valid IP Address.

1. From a computer, open an Internet web browser.
2. Enter the device's IP Address in the Address field, and then press Enter.
3. Click on the Properties tab. You may be prompted to login. Default account = 'admin', password = '1111'.
4. Click General Setup | Machine Software | Upgrades in the list of options on the left side of the window and verify that the checkbox for "Enabled" is checked
5. Click General Setup | Machine Software | Manual Upgrade in the list of options on the left side of the window.
6. Depending on the browser being used, click the Browse button, and then browse to and select the WorkCentre\_6400-system-sw#06107010328200#.DLM file.
7. Click the Install Software button to send the file to the device.

The browser will display a dialog once the file has been transferred to the device. A progress indicator is displayed on the front panel. Upon completion, the device will reboot. Xerox Internal Use Only Page 3 of 3  
Technical Support Operations

### Special Note: This release contains a new feature added under Services / Printing, entitled "Hold All Jobs"

The "Hold All Jobs in a Private Queue" feature requires Network Authentication be configured in order to identify individual user's jobs. If the Authentication Server type is configured for LDAP, please use the "Prepend Domain Name" feature found on the CWIS page: Properties -> Connectivity -> LDAP -> Custom Filters.

Example: mydomain\USERID. Without the Prepend Domain Name option, the Authenticated Users jobs will not be displayed at the LUI. Consult the System Administrators Guide for more information on Network Authentication and LDAP configurations.