

Mini Bulletin XRX16E WorkCentre 5325/5330/5335 SPAR Release 53.32.52



Bulletin Date: Feb 24, 2016

Purpose

This Bulletin is intended ONLY for the specific security problems identified below. The problems identified has been rated a criticality level of **IMPORTANT.**

Includes fix for:

 SSLv3.0 Poodle Vulnerability (CVE-2014-3566). SSLv3 supports an older encryption method that is no longer considered secure, and is no longer viable for protecting sensitive data in transmission over networks. This could allow a Man-in-The-Middle (MiTM) attack where a person on the network can force a "downgrade" of the session between a client and server to use SSLv3 instead of a more secure protocol such as TLS.

Fixed by disabling SSL and using TLS only.

Software Release Details

If your software is higher or equal to the versions listed below no action is needed.

Otherwise, please review this bulletin and consider installation of this version.

Model	Workcentre 5325/5330/5335
Firmware version	53.32.52
Link to Software Release	Available here

Installation Instructions

The Installation Instructions are as follows:

- 1. Extract / unzip the .bin file from the zip file you downloaded for this update to a known location.
- 2. Determine the currently installed software version as follows:
 - In CentreWare IS, click **Propeties > General Setup > Configuration**.
 - Scroll down to **Software** to verify the software version.
- 3. In CentreWare IS, click on **Properties > Services > Machine Software > Upgrades**.

© 2016 Xerox Corporation. All rights reserved. XEROX® and XEROX and Design®, ColorQube®, and WorkCentre® are trademarks of Xerox Corporation in the United States and/or other countries.

- 4. Under Upgrades select Enabled.
- 5. Click Apply.
- 6. Refresh your browser and navigate to **Properties > Services > Machine Software > Manual Upgrade**.
- 7. Under **Manual Upgrade**, click **Broswe** to locate and select the software upgrade fine in **.bin** format.
- 8. Click Open.
- 9. Click Install Software.

The file is sent to the printer. Once the software is installed the printer restarts.

10. Check the configuration report to verify that the software has updated.