

# Xerox Security Bulletin XRX19-020

## Xerox® FreeFlow® Print Server v9

For: Solaris® 10 Operating System

Install Method: DVD/USB Media

Deliverable: July 2019 Security Patch Cluster

Includes: Java 7 Update 231

Bulletin Date: August 11, 2019

## 1.0 Background

Oracle® delivers quarterly Critical Patch Updates (CPU) to address US-CERT Security vulnerabilities and reliability improvements for the Solaris Operating System. Oracle® does provide patches to the public but authorize vendors like Xerox® to deliver if there is an active FreeFlow® Print Server Support Contracts (FSMA). Customers that have an Oracle® Support Contract for their non-FreeFlow® Print Server Solaris Servers should only install patches prepared/delivered by Xerox®. Installing non-authorized patches for the FreeFlow® Print Server software violates Oracle® agreements, and can render the platform inoperable, and result in downtime and/or a lengthy re-installation service call.

This bulletin announces the availability of the following:

1. **July 2019 Security Patch Cluster**
  - This supersedes the April 2019 Security Patch Cluster
2. **Java 7 Update 231 Software**
  - This supersedes Java 7 Update 221 Software

**Notice:** The July 2019 Security Patch Cluster includes patches to mitigate the Meltdown and Spectre vulnerabilities. These vulnerabilities are not mitigated by the Solaris 10 OS patches alone. It is required to install a BIOS firmware update specific to the Xerox printer product and Digital Front End (DFE) platform (E.g., Dell model). Failure to install the Dell BIOS firmware will leave the FreeFlow® Print Server and Xerox printer product susceptible to breach of sensitive information using Meltdown and Spectre vulnerabilities. Dell does not deliver BIOS firmware to mitigate Meltdown and Spectre for PC platforms considered EOL (End of Life).

See US-CERT Common Vulnerability Exposures (CVE) the July 2019 Security Patch Cluster remediate in table below:

July 2019 Security Patch Cluster Remediated US-CERT CVE's					
CVE-2017-18258	CVE-2018-6467	CVE-2018-16329	CVE-2019-6467	CVE-2019-6469	CVE-2019-2804
CVE-2018-5743	CVE-2018-15607	CVE-2018-20467	CVE-2019-6468	CVE-2019-2787	CVE-2019-2832

See the US-CERT Common Vulnerability Exposures (CVE) the Java 7 Update 231 Software remediate in table below

Java 7 Update 231 Software Remediated US-CERT CVE's					
CVE-2019-2762	CVE-2019-2769	CVE-2019-2745	CVE-2019-2766	CVE-2019-2816	CVE-2019-7317

**Note:** Xerox® recommends that customers evaluate their security needs periodically and if they need Security patches to address the above CVE issues, schedule an activity with their Xerox Service team to install this announced Security Patch Cluster. Alternatively, the customer can install the Security Patch Cluster using the Update Manager UI from the Xerox® FreeFlow® Print Server Platform.

## 2.0 Applicability

The customer can schedule a Xerox Service or Analyst representative to deliver and install the Security Patch Cluster using media (DVD/USB). A customer can only perform the install procedures with approval of the Xerox CSE/Analyst. Xerox® offers an electronic delivery for “easy to use” install of a Security Patch Cluster, which is more suited for a customer to manage the quarterly patches on their own.

This Security patch deliverable has been tested on the FreeFlow® Print Server 93.10.04A software release. We have not tested the July 2019 Security Patch Cluster on all earlier FreeFlow® Print Server 9.3 releases, but there should not be any problems on these releases. It is always good practice to create a System Backup before installing the Security patches.

The Xerox Customer Service Engineer (CSE)/Analyst uses a tool (accessible from a secure FTP site) that enables identification of the currently installed FreeFlow® Print Server software release, Security Patch Cluster, and Java Software version. Run this tool after the Security Patch Cluster install to validate a successful install. Example output from this script for the FreeFlow® Print Server v9 software release is as following:

Solaris OS Version	10 Update 11
FFPS Release Version	9.0_SP-3_(93.10.04A.86)
FFPS Patch Cluster	July 2019
Java Version	Java 7 Update 231
Spectre Variant #1	Installed
Meltdown Variant #3	Installed
Spectre Variant #2	Not Installed

The July 2019 Security Patch Cluster is available for the FreeFlow® Print Server v9 release running on the Xerox® printer products below:

1. Xerox® iGen®4
2. Xerox® iGen®4 Diamond Edition®
3. Xerox® iGen®150 Press
4. Xerox® Versant® 80/180/2100 Presses
5. Xerox® Color 800/100 Press
6. Xerox® Color 800i/1000i Press
7. Xerox® Color Press J75/C75 Press
8. Xerox® Color Press 560/570 Production Printer
9. Xerox® Brenva® HD Production Inkjet Press
10. Xerox® Impika® Compact Inkjet Press
11. Xerox® CiPress® 325/500 Production Inkjet System
12. Xerox® D95/110/125/136 Copier/Printer
13. Xerox® Color 8250 Production Press

**NOTICE:** The July 2019 Security Patch Cluster includes patches to mitigate the Meltdown and Spectre vulnerabilities. These vulnerabilities are not mitigated by the Solaris 10 OS patches alone. It is required to install a BIOS firmware update specific to the Xerox printer product and Digital Front End (DFE) platform (E.g., Dell model). Failure to install the Dell BIOS firmware will leave the FreeFlow® Print Server and Xerox printer product susceptible to Meltdown and Spectre beaches to obtain sensitive information. Dell does not deliver BIOS firmware to mitigate Meltdown and Spectre for PC platforms considered EOL (End of Life).

## 3.0 Patch Install

Xerox® strives to deliver these critical Security patch updates in a timely manner. The customer process to obtain Security Patch Cluster updates (delivered on a quarterly basis) is to contact the Xerox hotline support number. Xerox Service or an analyst can install the Patch Cluster using a script utility that will support installing the patch cluster from the FreeFlow® Print Server hard disk, DVD, or USB media.

The Security Patch Cluster deliverables are available on a secure FTP site once they are ready for customer delivery. The Xerox CSE/Analyst can download and prepare for the install by writing the Security patch update into a known directory on the FreeFlow® Print Server platform, or on DVD/USB media. Delivery of the Security Patch Cluster includes an ISO and ZIP archive file for convenience. Once the patch cluster has been prepared on media, run the provided install script to perform the install. The install script accepts an argument that identifies the media that contains a copy of the FreeFlow® Print Server Security Patch Cluster. (e.g., # installSecPatches.sh [diskl dvd|usb]).

**Important:** The install of this Security patch update can fail if the archive file containing the patches is corrupted from file transfer or writing to DVD media. There have been reported install failures when the archive file written on DVD media was corrupt. Writing to media using some DVD write applications and media types could result in a corrupted Security Patch Cluster. The tables below illustrate Solaris checksums and file size on Windows for the Security Patch Cluster ZIP and ISO files. We provide these numbers in this bulletin as a reference to check against the actual checksum. The file size and check sum of these files on Windows and Solaris are as follows:

Security Patch File	Windows Size (Kb)	Solaris Size (bytes),	Solaris Checksum
Jul2019AndJava7U231Patches_v9.zip	2,294,293	2,349,355,572	4833 4588586
Julr2019AndJava7U231Patches_v9.iso	2,294,644	2,349,715,456	31071 4589288

Verify the **Jul2019AndJava7U231Patches\_v9.zip** file by comparing it to the original archive file size and checksum in the above table. Change directory to the file location (DVD media, USB, or hard disk) and type **“sum Jul2019AndJava7U231Patches\_v9.zip”** from a terminal window. The checksum value should be **“4833 4588586”**, and can be used to validate the correct July 2019 Security Patch Cluster on the DVD/USB.

## 4.0 Disclaimer

The information provided in this Xerox® Product Response is provided "as is" without warranty of any kind. Xerox® Corporation disclaims all warranties, either express or implied, including the warranties of merchantability and fitness for a particular purpose. In no event shall Xerox® Corporation be liable for any damages whatsoever resulting from user's use or disregard of the information provided in this Xerox® Product Response including direct, indirect, incidental, consequential, loss of business profits or special damages, even if Xerox® Corporation has been advised of the possibility of such damages. Some states do not allow the exclusion or limitation of liability for consequential damages so the foregoing limitation may not apply.